

MODEL - 49-07VOLUME CONTROL

<u>Circuit Designation</u>	<u>Value</u>	<u>Mfrs. No.</u>	<u>IRC No.</u>
R8	1 Meg.	R-312-1	13-137 Sw.No. 22
<u>CAPACITORS</u>		<u>AEROVOX</u> No.	
C1,C5,C10	.05 400v pp.		484
C2,C3,C6,C7	Tuning Gang	V-353-1	
C4,C14,C18	260 mmfd. mica		20% 1468
C11	50 mmfd. mica		20% 1468
C15,C19	.01 400v pp.		684
C16	4 mfd. 150v	G-332	PRT150
C17	.1 200v pp.		284
C20	.005 600v pp.		684
<u>MISCELLANEOUS</u>		<u>JENSEN</u> No.	
Speaker 4x6 PM	K-1047		P46V
Output Trans.	LK-423		2410
Osc. Coil	P-1405-3		
1st. I.F. Trans.	P-1843		
2nd. I.F. Trans.	P-1844		
Ant. Coil	P-1835		

MODEL - 49-08VOLUME AND TONE CONTROLS

<u>Circuit Designation</u>	<u>Value</u>	<u>Mfrs. No.</u>	<u>IRC No.</u>
R12	1 Meg.	R-312-1	13-137 Sw.No. 22
R18	75k	R-313-1	13-125
<u>CAPACITORS</u>		<u>AEROVOX</u> No.	
C1,C3,C4,C16	Tuning Gang	V-354-1	
C5,C26	.005 600v pp.		684
C6,C7,C18	50 mmfd. mica		1468
C9	2900 mmfd.		1467
C10,C27	.05 400v pp.		484
C11,C25	10 mfd. 150v		
	20 mfd. 150v	G-438A	PRT150
C14,C17,C19,C20	110 mmfd. mica		1468
C21,C23	260 mmfd. mica		1468
C22,C24	.01 600v pp.		684
<u>MISCELLANEOUS</u>		<u>JENSEN</u> No.	
Speaker 4x6 PM	K-1047		P46V
Output Trans.	LK-412-1		2410
1st. I.F. Trans.	P-1843		
2nd. I.F. Trans.	P-1844		
BC Ant. Coil	P-2023		
no osc. coil	P-2024		
SW Ant. Coil	P-2025		
SW Osc. Coil	P-2026		

BAYCREST MODEL-B-319
AIRLINE MODEL - L-319VOLUME AND TONE CONTROLS

<u>Circuit Designation</u>	<u>Value</u>	<u>Mfrs. No.</u>	<u>IRC No.</u>
R13	2 Meg.	R-297-1	18-139X Sw. No. 21
R15	150k	R-298-1	
<u>CAPACITORS</u>		<u>AEROVOX</u> No.	
C1,C2	Tuning Gang	V-319-2	
	Dual Padder	V-214	
	Dual I.F. Trimmer	V-228	
	Wavetrap Trimmer	V-263	
	R.F. Trimmers (4)	V-318	
C12,C31	50 mmfd. mica		20% 1468
C13,C14,C16,C17	.05 400v pp.		484
C18,C19	260 mmfd. mica		20% 1468
C20	.005 600v pp.		684
C21,C26	.01 600v pp.		684
C22,C28	.02 600v pp.		684
C23,C24,C25	25-20-40 mfd.		PRT 50
	50-450-450v	G-503	PRT450
C27	.003 600v pp.		684
C29	.05 600v pp.		684
C30	500 mmfd. mica		20% 1468
<u>MISCELLANEOUS</u>		<u>JENSEN</u> No.	
Speaker 10"	P-1620		Special
Field Coil 1050w	D-497		
Output Trans.	LK-424		2430
Power Trans. 35c	LK-429		1011
Power Trans. 60c	LK-430		1010
Wavetrap Coil	P-889		
with trimmer	P-890		
BC Ant. Coil	P-1673		
BC Osc. Coil	P-1674		
SW Ant. Coil	P-1675		
SW Osc. Coil	P-1676		
BC and SW Ant. and			
Osc. Coil and Trim-			
mer Assy.	P-1677		
1st. I.F. Trans.	P-1316-8		
2nd. I.F. Trans.	P-919-9		
Changer 60c	P-1705		
Cartridge	L-71		

MODELS - AIRLINE - L108A, L319A, L379
BAYCREST - B108A, B319A, B379VOLUME AND TONE CONTROLS

<u>Circuit Designation</u>	<u>Value</u>	<u>Mfrs. No.</u>	<u>IRC No.</u>
R13	2 Meg.	R-398-1	18-139X Sw. No. 21
R15	150k	R-298-1	
<u>CAPACITORS</u>		<u>AEROVOX</u> No.	
C1,C2	Tuning Gang	V-319-2	
C12,C31	50 mmfd. mica		20% 1468
C13,C14,C16,C17	.05 400v pp.		484
C18,C19	260 mmfd. mica		20% 1468
C20	.005 600v pp.		684
C21,C26	.01 600v pp.		684
C22,C28	.02 600v pp.		684
C23,C24,C25	25-20-40 mfd.		PRT 50
	50-450-450v	G-503	PRT450
C27	.003 600v pp.		684
C29	.05 600v pp.		684
C30	500 mmfd. mica		20% 1468
<u>MISCELLANEOUS</u>		<u>JENSEN</u> No.	
Speaker 10" PM	P-1762		P10T
Output Trans.	LK-424		2430
BC Ant. Coil	P-1673		
BC Osc. Coil	P-1674		
SW Ant. Coil	P-1675		
SW Osc. Coil	P-1676		
1st. I.F. Trans.	P-1316-8		
2nd. I.F. Trans.	P-919-9		
Wavetrap Assy.	P-890		
Choke Coil	LK-432		
Power Trans. 60c	LK-447		1010
Changer 60c	P-1769		